

Command	Command strings	Remark
PROGRAMMING	9a 02 01 00 0a aa a3	ENTER PROGRAMMING
UP	9a 02 01 00 0a dd d4	ID No. : 2 / Channel : 01
STOP	9a 02 01 00 0a cc c5	ID No. : 2 / Channel : 01
DOWN	9a 02 01 00 0a ee e7	ID No. : 2 / Channel : 01
DELETE PROGRAMMING	9a 02 01 00 0a a6 af	ENTER PROGRAMMING

PROGRAMMING	9a 03 01 00 0a aa a2	ENTER PROGRAMMING
UP	9a 03 01 00 0a dd d5	ID No. : 3 / Channel : 01
STOP	9a 03 01 00 0a cc c4	ID No. : 3 / Channel : 01
DOWN	9a 03 01 00 0a ee e6	ID No. : 3 / Channel : 01
DELETE PROGRAMMING	9a 02 01 00 0a a6 ae	ENTER PROGRAMMING

For Example: 9a 03 01 00 0a aa a2

Head code: 9a fixed head code, keep it	ID code: 03 ID code, write the ID number here for example ID1: 01 ID2: 02	Chanel code: 01 00 channel code, write the channel number here for example channel 1: 01 00 channel 2: 02 00 channel 16: 00 80	Command code: 0a aa command code, you could refer to above command code, it is fixed. for example up : 0a dd down: 0a ee	verify code: a2 verify code, it is a hexadecimal.
--	---	---	--	---



How to get Verify code?

in your PC there is calculator, choose hexadecimal version. As the photo shown

You could try to calculate the above verify code

verify code= ID code Xor channel code Xor command code

For example

03 Xor 01 Xor 00 Xor 0a Xor aa=a2